1、打开浏览器输入 IP,并点击继续浏览此网站。

\leftarrow \bigcirc	@ ttps://169.254.242.121/	▼ ℃ 搜索	P+ 6 ☆ 8
2 证书错误			
749 (E) 281	2013 ▼ @ 象和表加人则 包白旗 包2343244 包周玉 包大腸 包示法 包大服制制 包在线网彩 包》		
8	此网站的安全证书存在问题。		
	此网站出具的安全证书是为其他网头拖扯饭发的。 此网站出具的安全证书不是由受信任的证书颁发机构颁发的。		
	安全证书问题可能显示试图欺骗你或截获你向服务器发送的数据。		
	建议关闭此网页,并且不要继续浏览该网站。		
	◎ 单击此处关闭该网页。		
	◎ 继续浏览此网站(不推荐).		
	⊙ 详细信息		

2、输入账号, 密码空着, 点击确认。

服务器 169.2 Secure Acces	64.242.121 将要求你输入用户名和密 s。	码。 <mark>服务器</mark> 报告它来自
	admin 密码 V 记住我的凭据	
		确定

3、勾选静态 IP, 输入 IP 掩码网关, 输入数据库服务器 IP 地址等数据。



			addresses.
Basic Cent	tral Station/I	Host Communica	ations Setup
CS/Host Addressing	IP Address:	10 . 19 . 4 . 100	A number that network. This a access the Cen
	OR		
	⊖ Host Name:	8	An identifier u Station/Host o CSHost.Compa
Here I	Am Interval (sec):	20	The time inten message to a (填写2086400 seconds

4、保存控制器参数会提示创建控制器密码,密码需做修改

OR O Host Name:	An identifier used by the controller to access a Central Station/Host on a network. Example: CSHost.CompanyX.com
Here I Am Interval (sec): 20	The time interval in which a controller sends a Here I Am message to a Central Station/Host. Valid entry is 20 to 86400 seconds.
Login Password	
The login password for the adminusor has been set. Change Login Password	
	Submit

5、控制器需要打开端口,在web页面点击Advanced Setup。



Controller ODHCP Addressing

Static

Allows for DHCP (Dynamic Host Configuration Protocol) or maintains a Static IP ac a permanently assigned address) for the controller's network parameters. For Static the Controller Addressing information should be provided by the Ic

6、勾选选项,填写网域名称。

E Constanting in the	···	outside of the subnet of the controller. This address provides a communication link between the controller and external networks.
Primary DNS Server:		Primary Server that translates domain names into IP addresses.
Secondary DNS Server:		Alternate Server that translates domain names into IP addresses.
Network Broadcast: 1	0.19.255.255	The IP address used to broadcast messages to multiple local network devices.
Domain Name	CompanyX. com	A name that identifies a network. The domain name will be used to access a controller. Exampler CompanyX.com — 此处为网域名称
Host Name:	VertX_EV0_V1000	An identifier used to access a controller on a network by name.
FTP Enabled:	⊇Yes ● No	Enables or disables the controller FTP capability. Note that the Central Station/Host may need this enabled.
Telnet Enabled:	⊃Yes ●No	Enables or disables the controller Telnet capability. Note that the Central Station/Host may need this enabled.
SSH Enabled: 0	○Yes ◎No 勾选为Yes	Enables or disables the controller SSH capability. Note that the Central Station/Host may need this enabled.
SSL Enabled:	© Yes ◯ No	Enables or disables the controller SSL capability. Note that the Central Station/Host may need this enabled.
Virtual Port Enabled (169.254.242.121):	● Yes ◯ No	Alternate IP address for the controller. When the Virtual Port is enabled it provides a pathway to always contact the controller.

anced Central Station/Host Communications Setup

7、点击保存。

-		
(a) https://169.254.242.121/cgi-bin/setup.cgi?Type=ad	◇ ② 证书错误 ♂ 「 搬索…	P+ 🕅 🛠 🕮
Advanced Setup ×		
🍰 🗿 建议网站 👻 🗿 系统装机大师 🗿 百度 🗿 2345网址 🥘 海雪	al 🕘 天猫 🕘 京东 🗐 头条新闻 🗿 在线购彩 🗿 系统下载 🥘 VPN游戏加速 🗿 游戏娱乐 🗿 驱动精灵 🗿 系统优化大师	
	access the Central Station/Host. Example: 192.168.1.130	_
OR		
O Host Name:	An identifier used by the controller to access a Central Station/Host on a network. Example: CSHost.CompanyX.com	
Here I Am Interval (sec): 20	The time interval in which a controller sends a Here I Am message to a Central Station/Host. Valid entry is 20 to 86400 seconds.	
TCP/IP Connection Port: 4070	The port in which the Central Station/Host listens for an incoming controller connection. Valid entry is 1025 to 65535.	
TCP/IP Listen Port: 4050	The port in which the controller listens for an incoming Central Station/Host connection. Valid entry is 1025 to 65535.	
Encrypt Host Communication: O Yes No	Enable encrypted communication between the Controller and Host controllers.	
Encryption Key Seed Value: 2244668800	Seed from which the shared Controller/Host encryption key is derived. Valid entry is between 0 and 200 numeric values.	
Login Password		
The login password for the admin user has been set.	4.十.但,左	
Change Login Password	点击保存	
	Submit	
Copyright (c) 2010-2016 HID Global Corporation/ASSA ABLOY AB. At right This software is protected by copyright law and international treaties. Any	ts reserved.	
1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1 1		

8、点击保存。

